

# AC Direct 18w Downlight

**BritLED**  
*making a brighter world*



AC Direct Led Downlight with Seoul Semiconductor Array for internal use in Offices and Retail. Unique new AC direct Array means that there is no need for a driver just connects direct to AC lighting circuit and is surge protected to up to 3000v. Available in Warm White and Natural white direct from our wholesale network, bespoke colour temperatures are available. Manufactured in the UK and tested by the LIA to BS EN62560 standards, the AC direct downlight will be life tested under the new LIA Verified Scheme.

## Technical

Input Voltage:	230-240V AC
Led Type:	Seoul Semiconductor
Diffused Lumen Output:	WW1200LM, N1300LM, CW1400LM
Average Lumens Per Watt:	185Lm
Heatsink:	Thermal Conductive Polymer
Component Warranty:	3 years
Tested	BS EN62560
Material (Shell):	Aluminium
Size:	6"
Fixture Dimension:	195mm
Cut-Out:	165mm
CRI:	80
Manufactured:	Britain



**SEOUL SEMICONDUCTOR**

01246 208094

e. [info@brit-led.com](mailto:info@brit-led.com)

[www.Brit-led.com](http://www.Brit-led.com)